NexGen RIM Tach HT85 NorthStar™ brand

Hollow Shaft Encoder

Key Features

- Hollowshaft Design Mounts Easily to Large Motor Shafts, up to 4.50" in Diameter
- New Sensor Provides up to 0.075" of Air Gap, Over 50% More Than Competitive Models
- **Expanded Resolution up to 2400PPR**
- Redesigned Circuitry for On-Board **Diagnostics with LED and Alarm Output**
- Multiple Bore Sizes Available, Including **Tapered Shafts**
- Stainless Steel and Ductile Cast Iron Construction



ENVIRONMENTAL



Operating Temperature Range: -40°C to +85°C

Storage Temperature Range: -40°C to +120°C

Shock (Sensor Module): 30 G's Min

Vibration: 18 G's @ 5-2000 Hz spectrum

Humidity: Up to 98% (non-condensing)



SPECIFICATIONS

STANDARD OPERATING CHARACTERISTICS

Code: Incremental, Magnetic Pulses per Revolution: 60-2400 PPR

Phasing Sense: A leads B for Counter-Clockwise rotation (CCW) viewing encoder-mounted end

Quadrature Phasing: 90° ± 45° **Symmetry:** 50% ±15%

Number of Output Modules: Single or Dual

ELECTRICAL

Input Power Requirements: 5-26VDC, 95mA typical per sensor module, plus line driver load

Output Signals: IC-WE Differential Line Driver: 150mA, sink or source

Frequency Response: 0 - 180kHz Data & Index Noise Immunity: Tested to EN61326-1

Electrical Immunity: Reverse polarity and short

circuit protected

Connector: 10 pin industrial duty latching, sealed NEMA 4 &12, IP65. Optional MS3102 10 pin, Pigtail Cable, or Latching connector on cable extension

MECHANICAL

Bore Diameter: 1" to 4-1/2", straight or tapered

Mounting Configuration: Hollow Shaft mount

with Anti-Rotation Tether Shaft Speed: 3.600 RPM Shaft Length Required: 2.5" min Acceleration Rate: 3,600 rpm/sec max Allowable Shaft End-Play: 0.25" (Subject to

RPM Limitation)

Allowable Shaft Runout: 0.010" TIR (Subject to

RPM Limitation)

Housing Material: Cast Iron/Stainless Steel

Weight: 30 lbs

ELECTRICAL CONNECTIONS

Signal	Connector Pin	Pigtail Cable	MS 3102E18-IT#
Common	1	Black	A
В	2	Green	E
Α	3	Blue	D
Z *	4	Violet	C
Alarm †	5	_	F
Vcc +	6	Red	В
B	7	Yellow	H
Ā	8	Gray	G
Z *	9	Orange	l I
Shield	10	Braid	J


^{*} Index (Z) optional. See Ordering Information

[†] Alarm not available with Pigtail cable. See Ordering Information


NorthStar™ brand NexGen RIM Tach HT85

Ordering Information

To order, complete the model number with code numbers from the table below:



Note: See ACCESSORIES Section for Connectors and Spare Parts





Headquarters: 1675 Delany Road • Gurnee, IL 60031-1282 • USA

Customer Service:

Tel.: +1.800.873.8731 Fax: +1.847.662.4150 custserv@dynapar.com **Technical Support**

Tel.: +1.800.234.8731 Fax: +1.847.662.4150 northstar.techsupport@dynapar.com

European Sales Representative

Hengstler GmbH Uhlandstrasse 49, 78554 Aldingen Germany www.henastler.com